



## RXMOD-A1

### RX3000 4-channel Analog Module

The optional analog module has four analog inputs that support excitation power, scaling, and statistics measurements. These four, single-ended sensor inputs are configured through HOBOLink. A HOBO RX3000 is required for this product.



#### Key Advantages:

- 15-bit resolution and high accuracy
- Each module can have its own logging rate
- Input ranges up to 33V

## HOBO RXMOD-A1 Specifications

<b>Input Channels</b>	Four, single-ended, in addition to smart sensor data channels
<b>Measurement Range and Accuracy</b>	0–25.6 mA DC, $\pm 5 \mu\text{A} \pm 0.15\%$ of reading 0–2.5 V DC, $\pm 0.25 \text{ mV} \pm 0.2\%$ of reading 0–5 V DC, $\pm 0.25 \text{ mV} \pm 0.2\%$ of reading 0–10 V DC, $\pm 0.3 \text{ mV} \pm 0.2\%$ of reading 0–20 V DC, $\pm 0.6 \text{ mV} \pm 0.2\%$ of reading 0–33 V DC, $\pm 1.20 \text{ mV} \pm 0.2\%$ of reading
<b>Resolution</b>	15 bits
<b>Field Wiring</b>	Two- or three-wire via screw terminals, 16–24 AWG
<b>Minimum/Maximum Input Voltage</b>	0/33 V DC
<b>Minimum/Maximum Input Current</b>	0/25.6 mA
<b>Minimum Source Impedance for Current Measurement</b>	20 K
<b>Excitation Voltage</b>	12 V DC $\pm 5\%$ at 200 mA maximum per module

## Contact Us

Sales (8am to 5pm ET, Monday through Friday)

- ▶ Email [sales@onsetcomp.com](mailto:sales@onsetcomp.com)
- ▶ Call 1-508-759-9500
- ▶ In U.S. toll free 1-800-564-4377
- ▶ Fax 1-508-759-9100

Technical Support (8am to 6pm ET, Monday through Friday)

- ▶ Contact Product Support [www.onsetcomp.com/support/contact](http://www.onsetcomp.com/support/contact)
- ▶ Call 1-508-759-9500
- ▶ In U.S. toll free 1-877-564-4377

Onset Computer Corporation  
470 MacArthur Boulevard  
Bourne, MA 02532