

S-WCE-M003

Adapter for R.M. Young Wind Monitor for Wind/Alpine

Discontinued

Connects the R.M. Young Wind Monitor Sensor (model 05103) with Onset's line of research-grade weather stations, including the RX3000, U30-NRC, H21, and H22 systems.

Important Information

This adapter is not compatible with models 05103L, 05103V, 05103L-45, or 05103V-45

[View upgrade options](#)



Features

- Connects the R.M. Young Wind Monitor Sensor (model 05103) with Onset's line of research-grade weather stations

Contact Us

Sales (8am to 5pm ET, Monday through Friday)

- Email sales@onsetcomp.com
- Call 1-508-759-9500
- In U.S. toll free 1-800-564-4377
- Fax 1-508-759-9100

Technical Support (8am to 5pm ET, Monday through Friday)

- Contact Product Support www.onsetcomp.com/support/contact
- Call 1-508-759-9500
- In U.S. toll free 1-877-564-4377

Onset Computer Corporation
470 MacArthur Boulevard
Bourne, MA 02532

Adaptor for R.M. Young Wind Monitor for Wind/Alpine (S-WCE-M003) Specifications

Cable from adapter housing that plugs into logger: 3m (9.8 ft)

Adapter housing dimensions: 19.6 cm(7.7 in) long, 2.7 cm (1.05 in) diameter

Cable from adapter housing for connecting to screw terminal in the RM Young sensor junction box: 46 cm (18 in)

Wind speed range: 0 to 52 m/s (0 to 116 mph)

Wind speed accuracy (adapter only): 0.20 m/s (0.46 mph)

Wind direction range: 0 to 355 degrees

Wind speed resolution: 0.20 m/s (0.46 mph)

Wind direction accuracy (adapter only): 1.4 degrees

Wind direction resolution: 1.4 degrees